

TV entertainment and advertisements on One screen

SuperSign TV LX530S



The LX530S includes a built-in TV tuner to broadcast TV programs and deliver advertisements simultaneously. This affordable solution allows you to create content and manage displays using the SuperSign™ software. The 74 screen templates included with the display make it easier than ever for anyone to create dazzling content.

- Built-in speakers and TV tuner
- Wi-Fi Dongle Ready
- USB Plug and Play
- Fail Over
- SuperSign Lite/W/M/N/C Compatibility

Screen Sizes
42", 32H"



Simple Connectivity

With built-in SoC* and Wi-Fi dongle support, installation has been simplified. By removing the external media player and Ethernet/RS232C cables, the total cost of ownership (TCO) can be reduced.

* System on Chip



Fail Over

The USB failover function enables content to be displayed without dead spots when no input signal is available. It supports files in JPG format with a maximum file size of 10 MB.




Content Management

The SuperSign™ Solution includes SuperSign Lite, W, and C features to provide digital media editing, scheduling, distribution, and management capabilities. By installing SuperSign W on a server, you can manage up to 1000 TVs.

SuperSign™ Solutions

SUPER SIGN™ Lite

- Supports a single user and up to 50 clients
- Includes dedicated TV templates
- Features a playlist editor



TV entertainment and advertisements on One screen

SuperSign TV LX530S

Specifications

		LX530S
DISPLAY	Screen Size	42" / 32H"
	Type	LED (Slim Direct)
	Resolution	42": 1,920 x 1,080 (FHD) / 32H": 1,366 x 768 (HD)
	Brightness	300cd/m ²
BROADCASTING SYSTEM	Analog	PAL/NTSC-M
	Digital	DVB-C
AUDIO	Audio Output	10W + 10W
HOSPITALITY FEATURES		Welcome Screen (Splash Image, Video), Lock Mode, One Channel Map, Multi IR Code, Hotel Mode, USB Cloning, IR Out (RS-232C), USB Auto Play Back, External Speaker out, Real Time Clock
GENERAL FEATURES	Connectivity	MHL
	Management	Remote diagnostics / Self diagnostics
	Interactivity	HDMI-CEC (without ARC), HTNG-CEC
	RJP Interface	RS232C, HDMI CEC
	Auto Off / Auto Sleep	○
	Smart Energy Saving	○
	Anti-theft System	Kensington Lock
INTERFACE	Side	HDMI In, USB 2.0(2), Headphone Out (3.5mm Phone Jack)
	Rear	RF In, AV In (Composite), Component In (Y, Pb, Pr) + Audio (L/R), Digital Audio Out (Optical), RGB In (D-sub 15pin), PC Audio Input, RS-232C (D-sub 9pin), HDMI In, LAN (RJ45), Ext Speaker out (3.5mm Phone Jack)
ACCESSORY		L-CON, Power cord, CD title (Simple manual)
POWER	Voltage, Hz	100 ~ 240V, 50/60Hz
	Typical (Watts)	42" : 83.7W / 32H" : 59.0W
	Stand-by	42" : 0.26W / 32H" : 0.25W
STANDARD APPROVAL	Safety	CB, BIS, SIRIM, TISI, BPS, PSB, SNI
	Environment	CISPR
	Etc.	MEPS, Tick, EE, CIF, BEE, Freeview
SOFTWARE COMPATIBILITY		SuperSign Lite/W/M/N/C SuperSign Simple Editor (Available from Oct. 2015) *SuperSign W/M/N (Paid)

Dimension (unit : mm)




	42"	32H"
Set Size (With Stand, W x H x D, mm)	961 x 610 x 218	732 x 481 x 207
Set Weight (With Stand, Set, kg)	9.5	6.2
VESA Compatibility (mm)	400 x 400	200 x 200

Interface

42" / 32H"

- ① LAN
- ② OPTICAL DIGITAL AUDIO OUT
- ③ HDMI
- ④ EXTERNAL SPEAKER OUT
- ⑤ RGB IN
- ⑥ RS-232C IN
- ⑦ COMPONENT IN / AV IN
- ⑧ ANTENNA / CABLE IN
- ⑨ H/P OUT
- ⑩ HDMI IN 2(MHL)
- ⑪ USB IN



Download LG Commercial Display Mobile App



More info www.lgecommercial.com

YouTube youtube.com/c/LGECCommercialDisplay

LG may make changes to specifications and product descriptions without notice.
Copyright © 2015 LG Electronics Inc. All rights reserved. "LG Life's Good" is a registered of LG Corp.
The names of products and brands mentioned here may be the trademarks of their respective owners.

