



LX400

Quick Start Guide



Making a Direct
Connect® Call



Adding a Direct
Connect Group



Making a Group
Connect® Call



Sending a
Call Alert



Taking a Picture/
Recording a Video



Bluetooth®
Pairing




Sending All Contacts
via Bluetooth

 **Bluetooth®**



www.LGUSA.com

Getting to Know Your Phone



*Customizable.

To customize the DC Key, press **MENU OK** > **Settings (9)** > **Direct Connect (3)** > **Key Setup (6)**.

Making a Direct Connect Call*

Communicating is fast and simple with the LX400's Direct Connect feature. Enjoy instant, two-way “walkie-talkie” style conversations with this great phone.

1. From standby mode, press the **Right Soft Key** under **Contacts**.
2. Use the **Navigation Key** to highlight a DC user, then press and *hold* the **DC Key**.
3. Begin speaking after you hear the tone.
4. Release the **DC Key** once you're finished speaking.

Note: DC settings such as permissions, call alerts, group call options, headset mode, and key setup can be found under **Settings (9)**, then **Direct Connect (3)**. Headset mode (not for wireless headsets) allows you to set the call button on a headset to start either voice or DC calls. Key setup lets you customize the DC Key to bring up a list of recent DCs, place a DC call to the last caller, or DC call an assigned number.


**Direct Connect service may not be available in all markets.*



Adding a Direct Connect Group

Get in touch with multiple people at once! Take advantage of Direct Connect by linking contacts to form groups.

1. From standby mode, press the **Right Soft Key** under **Contacts**.
2. Press **MENU OK** to select **Add New**, and then choose **New Group**.
3. Press the **Left Soft Key** under **Start**.
4. Highlight a DC contact and press **MENU OK** to add him/her to the group. Repeat this process for everyone you want to include in the group.
5. Press the **Left Soft Key** under **Continue**.
6. Use the alphanumeric keypad to name your new group, then press the **Left Soft Key** under **Save**.



Making a Group Connect Call

Connectivity a priority? The LX400's convenient Group Connect feature gives you the ability to talk to up to 20 Direct Connect users at once.*

1. From standby mode, press the **Right Soft Key** under **Contacts**.
2. Use the **Navigation Key** to highlight a DC group, then press and *hold* the **DC Key**.
3. Begin speaking after you hear the tone.
4. Release the **DC Key** once you're finished speaking.




**Group Connect participants must also have a Nextel Direct Connect-capable Sprint device with the Group Connect feature. Group Connect is not interoperable with Nextel phones until late 2008.*

Sending a Call Alert

With the Call Alert feature, you can quickly send alerts to other DC users. You can even use the LX400's text templates to save time.*

1. From standby mode, press the **Right Soft Key** under **Contacts**.
2. Use the **Navigation Key** to highlight a DC contact, then press the **Left Soft Key** under **Msg/Alert**.
3. Select **Call Alert (1)**.
4. Scroll **left** or **right** with the **Navigation Key** to select a template message.
5. Press the **DC Key** to send the alert.






**Users must have a Nextel Direct Connect-capable Sprint device to receive the text.*

Taking a Picture/Recording a Video

Never be caught without a camera again! You're always ready with the easy-to-use LX400 camera and camcorder.


Flip Open

1. To take a picture, press and *hold* the **side**  **Key**.
To record a video, quickly press  and choose **Camcorder (2)**.
2. Press **left** or **right** on the **Navigation Key** to adjust brightness and **up** or **down** to adjust the zoom.* Press the **Right Soft Key** for more camera/camcorder options.
3. Press  to take the picture or start/stop recording.
4. To send your picture/video as a message, press the **Left Soft Key**.

Flip Closed

1. First, press .
2. Press and *hold*  to activate the viewfinder.
3. Press  to take the picture.


**Default camera setting of 960x1280 does not support zoom function.*



Bluetooth Pairing

Enjoy the freedom of Bluetooth wireless technology. The LX400 easily connects with headsets, phones, and more.

1. Set your Bluetooth accessory into pairing mode.*
2. Press **MENU OK**, then select **Tools (4) > Bluetooth (4)**.
3. Press **MENU OK** when prompted to turn on Bluetooth. Select **<Add New>** and then **Search**.
4. Once your Bluetooth device has been found, highlight it and press **MENU OK**.
5. Select **Add to Trusted (1)**.
6. Enter the passkey* (typically "0000" – 4 zeroes), and press **MENU OK** to pair.
7. Press **MENU OK** to continue.
8. To connect to the accessory, press **MENU OK**.
9. Select **Connect (1)**.





**Refer to your Bluetooth accessory's user manual for information about initiating pairing mode and the passkey.*

Sending All Contacts via Bluetooth

Transferring multiple contacts at once via Bluetooth is simple, making it convenient to share contact information with clients and friends – and you don't have to worry about typos!

1. From standby mode, press the **Right Soft Key** under **Contacts**.
2. Press the **Right Soft Key** under **Options**.
3. Press **MENU OK** to select **Send Contact (1)**.
4. Use the **Navigation Key** to highlight **All**, and then press **MENU OK**.
5. If prompted to turn on Bluetooth, press **MENU OK**.
6. Scroll **down** with the **Navigation Key** to highlight the device you want to send all contacts to and press **MENU OK** to send.



Optional Accessories

Maximize your phone with these cutting-edge accessories at www.LGUSA.com.



Bluetooth Headset (HBM-770)



Bluetooth Headset (HBM-760)



Headset



Extended Li-Ion Battery
(1,500 mAh)



Vehicle Power Changer



USB Cable

©2008 LG Electronics, Inc. All rights reserved. All other trademarks are property of their respective owners. All phone images are simulated. The Bluetooth® trademark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by LG Electronics is under license.



Mixed Sources

Product group from well-managed forests, controlled sources and recycled wood or fiber
www.fsc.org Cert no. XXX-XXX-XXX
© 1996 Forest Stewardship Council

